




CONDENSATOARE TRIFAZICE PENTRU COMPENSAREA ENERGIEI REACTIVE


Gama CLZ-FP - (tubular) 400 V, 50 Hz

Tip	Cod	kvar (50 Hz)		kvar(60 Hz) 400V	Greutate (kg)	Nici o acoperire	Dimensiuni(mm) (d x h)	Produs
		400V	440V					
Condensator trifazic, conectare papuci faston, gama clz-fpt (tubular) 50 Hz								
CLZ-FPT-44/2,5	[*] R20574	2	2.5	2.5	0.3	6	50 x 151	
CLZ-FPT-44/3	[*] R20575	2.5	3	3	0.3	6	50 x 151	
CLZ-FPT-44/5	[*] R20578	4	5	5	0.5	5	65 x 155	
CLZ-FPT-44/6,25	[*] R20579	5	6.25	6	0.7	4	75 x 155	
CLZ-FPT-44/7,5	[*] R2057A	6.25	7.5	7.5	1	4	75 x 215	
Condensator trifazic, conectare directa, gama CLZ-FP (tubular) 50 Hz								
CLZ-FP-44/10	[*] R2057C	8	10	10	1	1	85 x 245	
CLZ-FP-44/12,5	[*] R2057D	10	12.5	12	1.2	1	85 x 245	
CLZ-FP-44/15	[*] R2057E	12.5	15	15	1.3	1	85 x 245	
CLZ-FP-44/18,2	[*] R2057M	15	18.2	18	2	2	110 x 245	
CLZ-FP-44/20	[*] R2057F	16	20	20	2	2	110 x 245	
CLZ-FP-44/25	[*] R2057G	20	25	-	2.2	3	110 x 245	
CLZ-FP-44/30	[*] R2057H	25	30	-	3.3	-	136 x 220	
CLZ-FP-44/40	[c] R2057J	33	40	-	4.2	-	136 x 261	
CLZ-FP-44/50	[c] R2057K	41.3	50	-	5.5	-	136 x 355	


Gama CLZ-FP - (tubular), 230 V, 50 Hz, conectare directa

Tip	Cod	kvar (50 Hz)			kvar (60 Hz)		Greutate (kg)	Nici o acoperire	Dimensiuni(mm) (d x h)	Produs
		220V	230V	240V	220V	230V				
CLZ-FP-23/2,5	[c] R20514	2.3	2.5	2.7	2.7	3	1.2	1	85 x 175	
CLZ-FP-23/4	[c] R20517	3.7	4	4.4	4.4	4.8	1.6	1	85 x 245	
CLZ-FP-23/5	[c] R20518	4.6	5	5.4	5.5	6	1.6	1	85 x 245	
CLZ-FP-23/7,5	[c] R2051A	6.8	7.5	8.2	8.2	9	2.6	2	110 x 245	
CLZ-FP-23/10	[c] R2051C	9.1	10	10.9	11	12	2.6	2	110 x 245	
CLZ-FP-23/12.5	[c] R2051D	11.4	12.5	13.6	-	-	3.3	-	136 x 220	
CLZ-FP-23/15	[c] R2051E	13.7	23.8	-	-	-	3.3	-	136 x 220	

Gama CLZ-FP - (tubular), 460 V, 50 Hz, conectare directa

Tip	Cod	kvar(50Hz)			kvar (60 Hz)		Pentru Reactor	Greutate (kg)	Nici o acoperire	Dimensiuni(mm) (d x h)	Produs
		460V	440V	460V	480V	525V					
CLZ-FP-46/6,25	[c] R20589	6	6.6	7.2	R-5-400		0.9	1	85 x 175		
CLZ-FP-46/12,5	[c] R2058D	12.5	13.7	15	R-10-400		1.2	1	85 x 245		
CLZ-FP-46/15	[c] R2058E	15	16.5	18	R-12,5-400		1.4	1	85 x 245		
CLZ-FP-46/19	[c] R2058L	19	20.9	22.8	RB-15-400		1.9	1	85 x 245		
CLZ-FP-46/25	[c] R2058G	25	27.4	30	RB-20-400		2.1	1	85 x 245		
CLZ-FP-46/30	[c] R2058H	30	32.9	36.6	RB-25-400		3	-	136 x 220		

Gama CLZ-FP - (tubular), 525 V, 50 Hz, conectare directa

Tip	Cod	kvar (50 Hz)			kvar (60 Hz)		Greutate (kg)	Nici o acoperire	Dimensiuni(mm) (d x h)	Produs
		480V	525V	550V	480V	525V				
CLZ-FP-52/2	[c] R20553	1.7	2	2.2	2	2.4	1.2	1	85 x 175	
CLZ-FP-52/2,5	[c] R20554	2.1	2.5	2.7	2.5	3	1.2	1	85 x 175	
CLZ-FP-52/3	[c] R20555	2.5	3	3.3	3	3.6	1.2	1	85 x 175	
CLZ-FP-52/4	[c] R20557	3.3	4	4.4	4	4.8	1.2	1	85 x 175	
CLZ-FP-52/5	[c] R20558	4.2	5	5.5	5	6	1.2	1	85 x 175	
CLZ-FP-52/6,25	[c] R20559	5.2	6.25	6.8	6.2	7.5	1.2	1	85 x 175	
CLZ-FP-52/7,5	[c] R2055A	6.3	7.5	8.2	7.5	9	1.6	1	85 x 245	
CLZ-FP-52/8	[c] R2055B	6.7	8	8.7	8	9.6	1.6	1	85 x 245	
CLZ-FP-52/10	[c] R2055C	8.4	10	11	10	12	1.6	1	85 x 245	
CLZ-FP-52/12,5	[c] R2055D	10.4	12.5	13.7	12.5	15	2.2	2	110 x 220	
CLZ-FP-52/15	[c] R2055E	12.5	15	16.5	15	18	2.6	2	110 x 245	
CLZ-FP-52/20	[c] R2055F	16.7	20	22	20.1	24	2.6	2	110 x 245	
CLZ-FP-52/25	[c] R2055G	21.2	25	27.5	25	30	2.6	-	110 x 245	
CLZ-FP-52/30	[c] R2055H	25.4	30	33	30	36	2.8	-	136 x 220	
CLZ-FP-52/40	[c] R2055J	33.9	40	44	40	48	2.8	-	136 x 261	
CLZ-FP-52/50	[c] R2055K	42.4	50	55	50	60	2.8	-	136 x 355	

[*] Livrare imediata

[c] Livrare de consultat